APP-500BC

Six-zone network streaming PA mixer amplifier

AT A GLANCE

500 W RMS

6 Zones

Wi-Fi / Bluetooth

Six-zone network streaming PA mixer amplifier for installed audio applications.



Series reference image; an independent exact-model photograph was not provided.

TECHNICAL SPECIFICATIONS

Rated power (RMS)	500 W total
Zone outputs	6, with separate volume controls
Speaker outputs	70 V / 100 V / 4-16 ohm
Streaming	Wi-Fi 2.4 GHz / Bluetooth 5.0 / RJ45
Media inputs	USB up to 32 GB / AUX / optical-line switchable input
Microphone inputs	3; front MIC1 has priority
Tone controls	Bass / Treble / Master volume
Power supply	AC 230 V / 50 Hz
Frequency response	55 Hz-18 kHz

One amplifier power budget is shared by the six zones.