DCBE2250BC

Six-zone PA mixer amplifier with DC backup input

AT A GLANCE

250 W RMS

6 Zones

DC 24 V Backup

Six-zone PA mixer amplifier with DC backup input for installed audio applications.



Series reference image; an independent exact-model photograph was not provided.

TECHNICAL SPECIFICATIONS

Rated output power	250 W RMS total
Zone outputs	6, with volume controls
Speaker outputs	70 V / 100 V / 4-16 ohm
Inputs	MIC1 front / 2 MIC-LINE / 2 AUX rear
Player	Bluetooth / MP3 / FM
Frequency response	80 Hz-16 kHz
Distortion	0.5% at 1 kHz
AC supply	115 V / 60 Hz or 230 V / 50 Hz; selector
Backup supply input	DC 24 V